

Atlas Copco Generators

Designed to perform, built to last



QAS 20/25 (60 Hz)

With standard features that maximize safety and minimize environmental impact, the QAS 20/25 also features:

- Diesel power from the reliable Kubota engine
- Electrical power from Leroy Somer LSA series alternator
- Atlas Copco QC1002 control system
- 29 hours at 75% load fuel consumption

The QAS 20/25 line provides quieter operation, reduced emissions, and lower acquisition and operating costs.

www.atlascopco.com/portablepower

Sustainable Productivity

Atlas Copco

Technical Data

Model	QAS 20/25
Sound Pressure Level @ 23 feet @ 75% load	65 dB(A)
Fuel Tank Capacity	30 gal.
Fuel Consumption @ 75% load	1.04 gal/hr
Fuel Autonomy @ 75% load	29 hr

Engine	Kubota
Model	V2403
Rated Speed	1800 rpm
Emission Compliance	EPA IT4
Rated Output	29.6 HP @ 1800 rpm
Coolant	Water / Glycol
Cylinders	4
Displacement	2.4 L
Engine Control	Electronic

Alternator	Leroy Somer
Model	LSA40M5
Degree Of Protection / Insulation Class	IP23 / H

Dimensions and Weight	
Dimensions Skid (L x W x H)	70 x 33.5 x 46.5 in.
Weight - Skid Wet	1,868 lbs
Dimensions w/trailer (L x W x H)	110 x 59 x 57 in.
Weight - w/trailer Wet	2,121 lbs

Convenience Receptacles	
20 amp - 125 volt GFCI duplex	2
50 amp - 125 / 250 volt twist lock	2

The information contained herein is general in nature and is not intended for specific construction, installation or application purposes.

Generator Features and Options Include

Multi-Voltage Selector Switch	•
Remote Start / Stop	•
Digital Control System	•
110% Fluid Containment	•
Electronic Governor	•
Skid-Mount	○
Battery Charger	○
Coolant Heater	○
Ball Coupling	○
Spare Tire	○
Rear Stabilizer Jacks	○
Tool Box	○
External Fuel Connections	○

Standard •
Option ○

QAS 20	
Rated Standby Power	19.2 kW / 19.2 kVA
Rated Prime Power	17.3 kW / 17.3 kVA
Voltage Selections - 1Ø	120 / 240
Amperage Capacity @ 120 volts 1Ø	2 x 66 amps
Amperage Capacity @ 240 volts 1Ø	70 amps

QAS 25	
Rated Standby Power	22 kW / 22 kVA
Rated Prime Power	20 kW / 25 kVA
Voltage Selections - 3Ø	208/240/480
Amperage Capacity @ 208 volts 3Ø	69
Amperage Capacity @ 240 volts 3Ø	60
Amperage Capacity @ 480 volts 3Ø	30



Control Panel

A comprehensive instrument panel enables all key operating functions to be supervised without opening the canopy. Analog gauges provide at-a-glance monitoring. Protected by a tough transparent cover, the single panel provides easy start up and control of the generator. The panel also provides full system monitoring to ease operation.

Atlas Copco Construction Equipment

3700 East 68th Avenue
Commerce City, CO 80022 USA
Phone: +1 (303) 253-6922;
Fax: +1 (303) 217-2840
www.atlascopco.us



Use only authorized parts. Warranty or Product Liability does not cover any damage or malfunction caused by the use of unauthorized parts.

Atlas Copco